

**BANGLADESH UNIVERSITY OF BUSINESS AND TECHNOLOGY (BUBT)**  
**Faculty of Engineering and Applied Sciences**  
**Department of Electrical and Electronic Engineering**  
**Program: B.Sc. in EEE**  
**EEE 314: Digital Signal Processing I Lab**  
**(Section: 1; Shift: Day; Intake: 26)**

Lab Final

Fall 2021-22

Total Marks: 30

Time: 25 min.

---

Course Instructor: Sk. Hasibul Alam

---

- Q1.** If  $y[n] = x[n] * h[n]$ , determine  $Y(z)$  using convolution property of z-transform. Here,  $x[n] = [4 \quad \underline{3} \quad -7 \quad 9]$  and  $h[n] = [-6 \quad 9 \quad \underline{1} \quad 4]$ . [10]
- Q2.** If  $y[n] = x_1[n] - x_2[n]$ , plot  $y[n]$  using stem function. Here,  $x_1[n] = [4 \quad -7 \quad 3 \quad \underline{2} \quad -9]$  and  $x_2[n] = [2 \quad \underline{-5} \quad 4 \quad 3 \quad -4]$ . [10]
- Q3.** If  $x(t) = \sin(6200t) + 0.5 \sin(12500t)$  is sampled at 8 kHz, plot (using stem function) the magnitude spectrum of 300-point DFT of the sampled version. [10]

# Lab Final

## EEE 314: DSP 1 Lab

Total Marks: **30**Date: **19 November, 2020**

*\*Answer all the questions. Each question has 3 marks.*

*\*Write your name & student ID clearly on answer script, so that it's visible when taking photos by your camera.*

*\*After converting to single PDF on your mobile, open Google Classroom & upload it.*

Read the 'Note' section at the end of this page. Now write a code snippet (MATLAB) for each of the following questions:

- 1) Sample an analog  $(k + 30)$  Hz sine wave using  $(k + 250)$  Hz sampling frequency.
- 2) Plot a ramp sequence that is delayed by  $(k + 4)$ .
- 3) Decompose a unit-step sequence in odd & even part.
- 4) Find the cross-correlation between  $[9 \ 2 \ 3 \ 4]$  and  $[7 \ 9 \ \underline{(k + 1)} \ (k + 2) \ 3]$ .
- 5) Find the z-transform of  $[4 \ 6 \ 2 \ (k + 1) \ \underline{(k + 2)} \ 4 \ 5 \ 4]$ .
- 6) Find the inverse z-transform of  $X(z) = 2z / ((k + 2)z^2 - (k + 4)z + 9)$ .
- 7) Decompose the following using partial-fraction expansion:
 
$$X(z) = (k + 1)z / ((k + 2)z^2 - (k + 7)z + (k + 1))$$
- 8) Find the impulse response of an LTI system described by the following:
 
$$H(z) = (1 + (k + 1)z^{-1}) / (1 + (k + 4)z^{-1} + (k + 2)z^{-2})$$
- 9) Draw the pole-zero plot of an LTI system described by the following LCCDE:
 
$$y[n] = (k + 1)y[n - 1] + x[n] + (k + 3)x[n - 1]$$
- 10) Plot the following sequence:  $\text{sinc}(\pi n / (k + 6))$ .

**Note:** 'k' is the last digit of your student ID. You do **not** have to write or predict any output of your code. You also do **not** have to draw any figure or shape. Only the code snippet will suffice.

